

## Pérdidas en derivación (dB)

Ref.	Símbolo		Pérdidas en derivación (dB)														
			Bandas	Retomo	BI	Sub Banda	FM	S Baja	BIII/DAB	S. Alta Hiperb.	UHF	FI - SAT		Paso DC (350mA)	Pérdidas paso (dB)		
				5-47	47-68	68-89	88-108	104-174	174-230	230-446	470-862	950-2150	2150-2400		MATV	FI SAT	
<b>SCATV 5-1000 MHz</b>																	
5232			TV	<1	<1	<1	-	<1	<1	<1	<1	-	-	-	-		
			R	-	-	-	3	-	-	-	-	-	-	-	-		
5233			TV	<8	7	7	7	7	7	7	7	-	-	-	2.6	-	
			R	-	26	26	26	26	26	26	26	26	-	-		-	-
<b>Tomas con paso de corriente 5-2150 MHz</b>																	
5229			TV/R	4	4	4	4	4	4	4	4	4	5	-	SAT→IN	-	-
			SAT	4	4	4	4	4	4	4	4	4	5		-	-	-
5228			TV/R	8.5	8.5	8.5	8.5	8.5	8.5	8.5	8.5	8.5	9	-	IN→OUT	3.5	5
			SAT	7.5	7.5	7.5	7.5	7.5	7.5	7.5	7.5	7.5	10		SAT→IN		
5227			TV/R	13	13	13	13	13	13	13	13	13	13.5	-	IN→OUT	1.2	2
			SAT	13	13	13	13	13	13	13	13	13	14		SAT→IN		
5236			TV/R	20	20	20	20	20	20	20	20	20	24	-	IN→OUT	0.6	1.2
			SAT	20	20	20	20	20	20	20	20	20	24		SAT→IN		